

NRTZTT 系列內藏電容陶瓷諧振器



NRTZTT Series of Ceramic Resonator with Built-in Capacitor

Frequency Range: 1.80 ~ 50.00MHz

Application of Ceramic Resonator:

- Best choice for Remote control
- UPS
- Mouse



Electrical Specification:

Model	Frequency Range (MHz)	Frequency Accuracy (25℃)	Stability in Temperature (-20 ~ +80℃)	Operating Temperature (℃)	Aging For Ten Years (%)
NRTZTT□□□MG	1.80 ~ 6.00	±0.5%	±0.3%	-20 ~ +80	±0.3
NRTZTT□□□MT	6.01 ~ 13.00	±0.5%	±0.3%	-20 ~ +80	±0.3
NRTZTT□□□MX	13.0 ~ 50.00	±0.5%	±0.3%	-20 ~ +80	±0.3

DIMENSIONS(mm):

